

Oracle SBC SIPREC with Oreka TR Configuration Guide

Oracle SBC configuration

The Oracle SBC must be configured so that it points to Oreka recorder(s):

http://files.orecx.com/docs/oracle-sbc-call-monitoring-guide-sbc_scz740_monitoring.pdf

When configuring the session-recording-server, the protocol must be set to UDP.

Oreka orkaudio recorder configuration

After installing the orkaudio recorder as described in the Oreka TR Quick Start Guide, enable the sipua plugin in the `/etc/orkaudio/config.xml` file, and disable the default plugin:

`#vi /etc/orkaudio/config.xml:`

Ensure it looks like this:

```
<!--<CapturePlugin>libvoip.so</CapturePlugin-->  
<CapturePlugin>liborksipua.so</CapturePlugin>
```

Add this section, if not already present:

```
<SipUAPlugin>  
  <SipMode>SiprecAcme</SipMode>  
  <SdpOfferAnswerMode>true</SdpOfferAnswerMode>  
  <SupportFeatures>resource-priority,siprec</SupportFeatures>  
</SipUAPlugin>
```

Then restart orkaudio